

SRT 5492/SRT 5495 Software Update Feature Additions

1. Timer Lead In/Lead Out Times

- You can now set lead in and lead out times for timers set via the EPG or manually. In the Time Settings Menu you can set lead in and lead out times of 5, 10 or 15 minutes. This time will automatically be added to the beginning and/or end of all recordings set via the EPG or manually.

2. Active/Passive Standby

- You can now set the Standby Mode to either Power Saving or Normal via the Front Display Settings in the Menu. Select Normal if want the antenna signal to be passed to your TV or Power Saving to use less power while in Standby.

3. Rotate Jpegs

- You can now Rotate Jpeg images you are viewing via your **STRONG DVR**. Simply press the Blue key on the remote control to rotate the image to be displayed in the correct aspect.

4. Auto Timeshift/Timeshift Record Time

- Time Shift can now be selected to be permanently ON or activated by pressing the Pause button during live viewing. The Timeshift duration can also be adjusted between 10, 30, 60, 90 and 120 minutes via the Menu under Disk Manager. Please note that the Timeshift will restart when the channel is changed.

5. Adjustable Skip Time

- You can now adjust the amount of time you skip through a recorded program when you press the Page Up and Page Downs Keys. Via the Menu under Disk Manager you can select Skip Times of either 5, 10 and 30 seconds or 1, 2, 3, 5, 10, 20 and 30 minutes.

6. PIP (Picture in Picture)

- **SRT 5492 and SRT 5495** now offer PIP. Picture in Picture allows you to watch one program in full screen mode and another channel in a small window in the top right hand corner of the screen. To activate PIP press the Advance Key. A Sub Channel List will appear. Then simply select the channel you wish to view in the PIP window by pressing ok. To select a different channel for the PIP window, press the Blue Key, this will display the Sub Channel List and you can then select the new channel by pressing ok. To swap the programs in the main screen and the PIP screen press the Recall key on the remote control. To decrease the size of the PIP window pres the Advance key. Press the advance key a second time stop the PIP feature

7. File Descriptions in File Manger Menu

- Files that have been recorded by the unit are accessible in both the File List section and the File Manger section in the Records folder. In the Records folder the files are labeled in a clearer format. E.g. a program that was recorded on the 30th March 2010 at 11:00am on ONE HD will be displayed as –
(ONE HD) @110000_30MAR2010

8. File Cut Feature

- You are now able to cut sections out of recorded programs. While playing back a recorded program press the Info Key twice. This will bring up a menu at the bottom of the screen. The Blue Key refers to the File Edit function. Pressing the Blue key will place the unit into the File Edit mode. Pressing the Ok key will input the start position of the file to be cut or copied. A small window will be displayed in the top left hand corner showing the time and frame of the when the cut was started. You can now fast forward or skip to the desired position you wish cut or copy. Press the Ok key to mark the end of the section to be cut or copied. You will then be asked whether you wish to Cut or Copy. By selecting Cut the selected portion will be deleted. Selecting Copy allows you to create this portion into a separate file in the File List. This file will be listed by the same name as the original file but will have E and digit in front of the name (e.g. E2-ONE HD)

